Dialog3G CellularTM 500 Remote Small Concentrator



The Dialog3G Cellular[™] 500 (DC500) is a self powered unit for cellular metering and control. The DC500 functions as a small concentrator for up to 500 water meters. The DC500 can support the following alerts: Leaks, Tamper, High and low flows, Water level and pressure, Low battery indication, Meter reading indication and CCW alarm.



Applications

The DC500 can be connected to Dialog 3G water meters. With its built in GPRS Modem, the DC500 uses available cellular networks for transmitting metering data to the Dialog3G control center. This self powered unit can transmit its accumulated data several times each day, subject to programming.

Features

- Collects up to 500 3G meters via RF link
- Quad band cellular network support
- Remote parameters programming
- Remote server time synchronization
- Local diagnostics RS232/USB connection

Specifications 3SI

- Mode Receive Only
- Frequency IL/WB 916.3 MHz /EU 868.3 MHz / IN 866.1 MHz
- Modulation FSK
- Sensitivity (10% PER, 128bits packet length) -99dBm
- Selectivity @ 1MHz 50dB
- Selectivity @ 5MHz 70dB
- Error Detection Yes
- Error Correcting Up to 3 Errors
- Receiver Current 40mA



AMR/AMI

LIRBAS

Arad Ltd. Dalia 1923900, Israel, Tel: 972-4-9897911, Fax: 972-4-9897960, www.arad.co.il



Dialog3G Cellular[™] 500 Remote Small Concentrator

Technical

Parameters	Description
Description	DC-500 Concentrator
Input Connection Type	Serial connection (RS232/USB)
Box Size	160x130x60mm
Unit weight	2 Batteries power: 1150 grams 8 Batteries power: 1800 grams (External Antenna)
Power Supply	Battery: 2/8 Lithium Batteries, "D" size
Operational Life	5 years (calculated for default use, one transmit a day with 2 batteries)
Protocols	TCP/IP over GPRS, Text/UDP for SMS
Transmission Standards	UMDS GPRS/GSM
Frequencies	800/900/1700/1800 MHz
Configuration Storage	Non-volatile memory
GPRS Standards	ETSI ITU-T
Environmental	IP-67

For the most updated version, please view our website: www.arad.co.il Specifications are subject to change without notice.





AMR/AMI and accessories

For the most updated version, please view our website: www.arad.co.il Specifications are subject to change without notice.